



## Confidea CHT

Confidea Charging Tray



### Description

The Confidea Charging Tray is a rack-mountable 3 U high container that can recharge 6 Confidea Battery Packs at once. It has an auto-ranging power supply and a loop-through mains connector. A maximum of 4 chargers can be daisy-chained for 110 VAC regions and 8 for 220 VAC regions. It is designed for multiple mounting possibilities, having 19" rack, wall or table mounting capabilities.

Battery packs can be fully charged in 4 hours or quick charged to reach 50% capacity in 1 hour.

### Features

- Loop-through mains connector
- 6 slots for 1 Confidea Battery Pack each
- 19" rack mountable

### Certifications

Region	Certification
Europe	CE

### Specifications

Mechanical	
Material	PC/ABS 1 mm steel
Color	RAL 9011
Size (mm)	130 (w) × 480 (h) × 140 (d)
Size packed (mm)	255 (w) × 540 (h) × 265 (d)
Weight (g)	3920
Weight packed (g)	4860
Electrical	
Supply voltage	100-230 VAC ±10%
Output power	200 W
Supply voltage	100-230 VAC ±10%
Environment	
Operating temperature	-10 to 60 °C

All information copyright **Televic Conference**, 2015. Version 1.0, October 2015

—  
 Leo Bekaertlaan 1 · 8870 Izegem · Belgium  
 Tel. +32 51 30 30 45  
 Fax +32 51 31 06 70  
 E-mail: [conference@televic.com](mailto:conference@televic.com)  
 Web: <http://www.televic-conference.com>  
*Televic reserves the right to change this document without notice.*