


peerAir™ | pro Wireless AV Multi-Display System

When running cables is not an option, stream HD content wirelessly with the PeerAirTM Pro Wireless AV Multi-Display System. With four inputs and the ability to multicast to up to six displays, this wireless workhorse streams Full HD 1080p and passive 3D signals up to 210ft (64m) to an HDTV, projector or any other display. For new installations and retrofits alike, this kit is a time-saving tool for professional AV integrators in both commercial and residential applications.

The Peerless-AV® PeerAir™ Pro Multi-Display System provides Full HD 1080p streaming for up to six displays.

Additional Features

- Full HD 1080p (60Hz) (24/30 fps) and passive 3D signal flow, ideal for ultra-fast signal streaming
- Long range, high-quality streaming up to 210ft (64m)* with no reduction of picture quality
- Multicast up to six PeerAir™ Pro Wireless Receivers**
- Transmits through walls and ceilings for multi-room streaming capability
- The PeerAir™ Pro (802.11n) creates it's own network without interfering with existing WiFi networks
- Built-in IR does not require line-of-sight placement to control source devices such as a DVR/ set-top box, satellite box, Blu-ray®/ DVD player, media server, VCR or game console
- Plug and play set up requires no software or driver installation




BUILT-IN IR CONTROLS SOURCE DEVICES

Without need for line-of-sight device placement

Makes it easy to fit the PeerAir $\ensuremath{^{\text{TM}}}$ Pro units into any application

*Actual distance will be reduced with obstructions between transmitter and receiver models.



Transmitter back

Plug in up to four (4) AV source devices and easily switch between them with the included remote control





Three (3) output port options available ideal for virtually any output device







^{**}Requires additional receiver units.

Model Numbers

HDS300-EUK PeerAir[™] Pro Wireless AV Multi-Display System HDS300-2-EUK Multicast: Two PeerAir™ Pro Wireless Receivers HDS300-3-EUK Multicast: Three PeerAir™ Pro Wireless Receivers HDS300-4-EUK Multicast: Four PeerAir™ Pro Wireless Receivers HDS300-5-EUK Multicast: Five PeerAir™ Pro Wireless Receivers **HDS300-6-EUK** Multicast: Six PeerAir™ Pro Wireless Receivers

INPUTS (TRANSMITTER) 3 x HDMI 1 x HDMI Pass-Thru 1 x VGA: High Density 15-Pin D-Sub (RGB) 1 x Component & Composite (via included dongle) AUDIO IN: -1 x 3.5mm Audio Jack 1 x IR Port x LAN (Ethernet): RJ45 Jack



Product Specifications

Package Specifications

VIDEO INPUT (Transmitter)	- 3 x HDMI up to 1080p (60Hz) -1 x VGA: High Density 15-Pin D-Sub (RGB) -1 x Composite (via included dongle) -1 x YPbPr Component (via included dongle		
VIDEO OUTPUT (Receiver)	- 1 x HDMI up to 1080p (60Hz) - 1 x Composite - 1 x YPbPr Component		
VIDEO OUTPUT (Transmitter)	- 1 x HDMI up to 1080p (60Hz)** (Via Pass-thru Port)		
ENCODING	- H.264 Baseline Profile with Level 4.2 - HDCP Compliant		
WIRELESS CONNECTION	- Supporting IEEE 802.11n: OFDM		
WIRED CONNECTION	- RJ45 LAN Port - Direct Connection (LAN Cable)		
LAN	- 1 x LAN Port (Transmitter and Receiver) - 10/100/1000 Base		
USB	- 1 x USB Type A Female (Transmitter and Receiver)		

AUDIO	- 2 Ch. Linear PCM, - Analog, 48kHz 16-bit ADC
AUDIO INPUT	- 1 x 3.5mm Audio Jack
AUDIO OUTPUT	- 1 x 3.5mm Audio Jack - 1 Stereo RCA Audio Jack (Receiver)
POWER	- Voltage: 120V AC, 60Hz - Consumption: 12V DC, 2A
VIDEO RESOLUTION	- 480i/p, 720p, 1080i and 1080p (24/30fps)
VIDEO STREAMING	- 40mS Latency
FREQUENCY	- 5.18 - 5.25GHz & 5.75 - 5.81GHz
LAN CONNECTION	- 10/100/1000 Base
RANGE	- 210ft (64m)
BROADCAST	- 1 Transmitter to 6 Receivers*
SECURITY	- WPA2 Personal and AES

ANTENNA TYPE	- 2 x Internal Antenna (Transmitter and Receiver) - MIMO Interface			
IR FLASHER	- 3 IR Flashers			
IR EXTENDER	- 1 IR Extender			
REMOTE CONTROL	- 17 button IR remote			
LEDS	- Port ID 5 x LED on Transmitter; 3 x LED on Receive - Power On 1 x LED (Transmitter and Receiver) - Link 1 x LED (Transmitter and Receiver)			
COLOR	- Black			
HOUSING CASE	- Plastic			
UNIT SPECIFICATIONS	- Dimensions (W x H x D): 1.25" x 7.63" x 4.5" (31 x 193 x 114mm) - Unit Weight 1.36lb (0.62kg) - Unit Weight w/accessories: 2.32lb (1.05kg)			
MASTER PACK SPECIFICATIONS HDS300-EUK (Quantity of 9)	- Master Pack Qty: 9ea - Dimensions (W × H × D): 20" x 9.4" x 15.6" (508 x 239 x 396mm) - Ship Weight: 31.52lb (14kg)			

^{*} Multicast models available (HDS300-2,-3,-4,-5,-6)
** From HDMI 1 input only

	PACKAGE SIZE (W x H x D)	PACKAGE SHIP WEIGHT	PACKAGE UPC CODE	PACKAGE CONTENTS	UNITS IN PACKAGE
HDS300-EUK	6.53" x 5" x 8.46" (166 x 127 x 215mm)	4.7lb (2.13kg)	735029310792	1x Transmitter, $1x$ Receiver, $2x$ Stands, $1x$ Remote control, $1x$ IR Flasher, $1x$ IR Extender, $1x$ Component adaptor, $2x$ Power adaptors	1
HDS300-2 -EUK	10" x 10" x 10" (254 x 254 x 254mm)	6.4lb (2.9kg)	735029310808	1 x Transmitter, 2 x Receivers, 3 x Stands, 2 x Remote controls, 1 x IR Flasher, 1 x IR Extender, 1 x Component adaptor, 3 x Power adaptors	1
HDS300-3-EUK	10.625" x 9.75" x 13" (270 x 248 x 330mm)	8.3lb (3.18kg)	735029310815	1 x Transmitter, 3 x Receivers, 4 x Stands, 3 x Remote controls, 1 x IR Flasher, 1 x IR Extender, 1 x Component adaptor, 4 x Power adaptors	1
HDS300-4-EUK	10.625" x 9.75" x 13" (270 x 248 x 330mm)	10.1lb (4.18kg)	735029310822	1 x Transmitter, 4 x Receivers, 5 x Stands, 4 x Remote controls, 1 x IR Flasher, 1 x IR Extender, 1 x Component adaptor, 5 x Power adaptors	1
HDS300-5-EUK	14.875" x 9.375" x 11.375" (378 x 238 x 289mm)	12.35lb (5.6kg)	735029310839	1 x Transmitter, 5 x Receivers, 6 x Stands, 5 x Remote Controls, 1 x IR Flasher, 1 x IR Extender, 1 Component adaptor, 6 x Power adaptors	1
HDS300-6-EUK	14.875" x 9.375" x 11.375" (378 x 238 x 289mm)	14.2lb (6.44kg)	735029310846	1 x Transmitter, 6 x Receivers, 7 x Stands, 6 x Remote controls, 1 x IR Flasher, 1 x IR Extender, 1 x Component adaptor, 7 x Power adaptors	1

Accessories


HDS300-R-EUK: PeerAir™ Pro Wireless Receiver***

HDS-ASE: Wireless Tx/Rx Security Enclosure for use with PeerAir™ Pro Models


Wall Shelf for use with PeerAir™ Pro models

*** Requires transmitter and push button scan pairing.

All dimensions = inch (mm)







TOP VIEW FRONT VIEW SIDE VIEW

Architect Speci Mcations

The PeerAir™ Pro Wireless AV Multi-Display System shall be a Peerless-AV model HDS300-EUK, HDS300-2-EUK, HDS300-3-EUK, HDS300-4-EUK, HDS300-5-EUK, HDS300-5 HDS300-6-EUK and shall be located where indicated on the plans. Assembly and installation shall be done according to instructions provided by the manufacturer.

Visit peerless-av.com to see the complete line of AV solutions from Peerless-AV, including outdoor displays, wireless, kiosks, digital audio, display mounts, projector mounts, carts/stands, and a full assortment of accessories.

Peerless-AV 2300 White Oak Circle

Aurora, IL 60502 USA

(800) 865-2112 (630) 375-5100 Fax: (800) 359-6500

Peerless-AV Europe

Unit 3 Watford Interchange Colonial Way, Watford Herts, WD24 4WP United Kingdom

+44 (0) 1923 200100 Fax: +44 (0) 1923 200101

Peerless-AV de México

Ave de las Industrias 413 Parque Industrial Escobedo Escobedo, N.L., Mexico 66050

+52 (81) 8384-8300 Fax: +52 (81) 8384-8360

